



EMERGENCY ADD-ON KIT

FOR SINGLE OCCUPANCY RESTROOMS

LEARN MORE



click or scan

CERTIFICATIONS



DESCRIPTION

BEA's **EMERGENCY ADD-ON KIT** is designed to be used in single occupancy restrooms where someone may require emergency assistance.

It can be used in conjunction with BEA's **RESTROOM KIT** or as a standalone solution. It is designed to meet building codes requiring an emergency request system.



For Outside Signaling

"ASSISTANCE REQUIRED" signal (LED + adjustable sounder)

Combined Unit For Ease Of Installation

"PUSH FOR EMERGENCY ASSISTANCE" Button + Indicator (LED + selectable sounder)



Signage Available In English And French

Double-sided signage offers French and English emergency notice

Code Compliant

Ontario Regulation 368/13 compliant

APPLICATIONS



Emergency Application



Single Occupancy Restroom

TECHNICAL SPECIFICATIONS

10ARS

Lamp Voltage Rating	28 VAC / VDC
Sounder Voltage Rating	16 – 24 VAC / VDC
Sounder Current Rating	15 mA
Lamps	Miniature bayonet type (#313)
Mounting	Fits standard single-gang
Sounder & Lamp Terminal	2 pigtail wires (each)
Material	Stainless steel & Polycarbonate
Dimensions	
Single Gang Faceplate	2 3/4" (W) × 4 1/2" (H)
White Lens (B-31695)	2 1/4" (W) × 4" (H) × 3 1/8" (D)


10EBUTTONCOMBO

Voltage	12 – 24 VAC / VDC ±10%
Indication	Audible buzzer (selectable on / off) and visual LED
Text Inserts	10
Button	E-stop button Push On / Pull Off
Material	Stainless steel & Polycarbonate
Accessory	Rubber weather gasket included
Certifications	FCC

70.5675

Material	Polystyrene
Dimensions	12" (W) × 5 1/2" (H)
Language	Double-sided French / English

PRODUCT SERIES



DISCLAIMER Information is supplied upon the condition that the persons receiving it will make their own determination as to its suitability for their purposes prior to use. In no event will BEA be responsible for damages of any nature whatsoever resulting from the use of or reliance upon information from this document or the products to which the information refers. BEA has the right without liability to change descriptions and specifications at any time.

WWW.BEASENSORS.COM



BEA AMERICAS / RIDC Park West / 100 Enterprise Drive / Pittsburgh, PA
T 1-800-523-2462 / F 1-888-523-2462 / E info-us@BEAsensors.com

A Halma company