



- NOTES: 1) JUMPERS ARE PLACED ON J1 PINS 1&2, J2 PINS 4&5 FOR DRY CONTACTS ON RELAY OUTPUT #1.
 2) PUSH PLATE, MOTION SENSOR, CARD READER MUST BE DRY CONTACT.
 3) TRANSFORMER AND BRIDGE RECTIFIER VOLT/ AMPERE RATING IS DETERMIND BY CURRENT DRAW OF ELECTRIC PANIC.
 4) MAGNETIC REED SWITCH MUST BE CLOSED WHILE DOOR IS OPEN.
 5) SET MC-10 TIME DELAY FOR THE LENGTH OF TIME TO KEEP PANIC UNLOCKED ONCE CLOSED. IF PANIC CURRENT LOAD IS GREATER THAN 500 mA, AN AUXILLARY RELAY MUST BE USED. PLEASE CONTACT BEA TECHNICAL SERVICES FOR MORE INFORMATION.

IF AFTER TROUBLESHOOTING A PROBLEM, A SATISFACTORY SOLUTION CANNOT BE ACHIEVED, PLEASE CALL B.E.A., INC. FOR FURTHER ASSISTANCE DURING EASTERN STANDARD TIME AT 1-800-523-2462 FROM 8AM - 5PM. FOR AFTER-HOURS, CALL EAST COAST: 1-866-836-1863 OR 1-800-407-4545 / MID-WEST: 1-888-308-8843 / WEST COAST: 1-888-419-2564. DO NOT LEAVE ANY PROBLEM UNRESOLVED. IF YOU MUST WAIT FOR THE FOLLOWING WORKDAY TO CALL B.E.A., LEAVE THE DOOR INOPERABLE UNTIL SATISFACTORY REPAIRS CAN BE MADE. NEVER SACRIFICE THE SAFE OPERATION OF THE AUTOMATIC DOOR OR GATE FOR AN INCOMPLETE SOLUTION.WEB: WWW.BEASENSORS.COM

BEA
 We open up New Horizons
 HALMA GROUP COMPANY
 100 ENTERPRISE DRIVE
 PITTSBURGH, PA 15275
 PHONE: (412) 249-4100
 FAX: (412) 249-4101
 EMAIL: www.beasensors.com

**TITLE: MC-25 WITH ELECTRIC PANIC,
 PUSHPLATE AUTOMATIC DOOR
 APPLICATION**

SIZE: A	DRAWN BY: KJG	REV BY: JDC	PART NO: 80.0142.02
	SCALE: NONE	DATE: 20 MARCH 2006	SHEET 1 OF 1