



ACCESS CONTROL PUSH BUTTON

ILLUMINATED, REQUEST-TO-EXIT BUTTON



PRODUCT



[Go to the product page](#)

DESCRIPTION

BEA's **ACCESS CONTROL PUSH BUTTON** is part of the request-to-exit product line, including presence sensors, power supplies, ruggedized **PNEUMATIC PUSH BUTTONS**, heavy duty **PIEZO BUTTONS**, **ACCESS KEYPADS**, a complete range of **MAGLOCKS** and other devices designed for controlled access applications.

BEA's **ACCESS CONTROL PUSH BUTTON** is an illuminated access control solution, consisting of a stainless steel faceplate and brightly lit plastic button. It is appropriate for most indoor and low-ambient light applications.




Easy To Maintain

Easily replaced 12 – 24 VAC / VDC light bulb, reducing whole-product replacement

Highly Durable

Stainless steel faceplate



Vandal Resistant

Vandal / tamper resistant design

APPLICATIONS



Request-To-Exit

TECHNICAL SPECIFICATIONS

Technology	Mechanical switch and light socket
Faceplate Dimensions	Single Gang - 2 3/4" (W) x 4 1/2" (H)
Visual Style	Illuminated Green button that signals activation, which can also be disabled
Materials	Stainless steel faceplate with tamper-resistant screws
Input Power	10 A @ 125 / 250 VAC
Time Range	Momentary switch, no delay
Bulb Power	
High Volt Bulb	60 mA @ 24 VDC (P/N C656)
Low Volt Bulb	190 mA @ 12 VDC (P/N CM-161)
Relay	SPDT, color coded wiring (Open / Closed)

PRODUCT SERIES



10ACPBSS1
Single gang
request-to-exit button



10BOX24SGSM
Standard surface
mount box

DISCLAIMER Information is supplied upon the condition that the persons receiving it will make their own determination as to its suitability for their purposes prior to use. In no event will BEA be responsible for damages of any nature whatsoever resulting from the use of or reliance upon information from this document or the products to which the information refers. BEA has the right without liability to change descriptions and specifications at any time.

WWW.BEASENSORS.COM



BEA AMERICAS / RIDC Park West / 100 Enterprise Drive / Pittsburgh, PA
T 1-800-523-2462 / F 1-888-523-2462 / E info-us@BEAsensors.com

A **Halma** company